

CAR RADIO CURITIBA 120



Order Number
1 011 700 000 100

Highlights

- **Radio**
AM/FM Tuner
- **Media player**
Playback formats: MP3, WMA, WAV, FLAC
MP3 / WMA comfort browsing
- **Data carrier**
USB
- **Inputs**
Front USB (Standard A-type)
Front Aux-in
- **Bluetooth**
Built-in Bluetooth for hands-free calling and audio streaming. Built-in microphone.
- **Amplifier**
2-channel Preamp-out
4 x 20 Watt Max. power
- **Equalizer**
Sound presets (Rock, Pop, Classic)
- **General**
Fixed panel

CAR RADIO

CURITIBA 120

BLUETOOTH

Supported version	Bluetooth 4.2
Supported profiles	HFP, HSP, A2DP, AVRCP
Pairing (number of devices)	1
Pairing code	0000
Hands-free calling	via micro + radio speakers
Microphone	Built-in
Key functions	accept / hang up / reject call

RADIO

Type of tuner	analog
Wave bands	AM 1, 2 , FM 1, 2, 3
Station memory	30
Sensitivity	lo/dx
Frequency response (Hz) -3dB	30 – 15.000

DATA CARRIER

USB-removable storage	USB 2.0 compatible
Formatting USB, SDHC, SD	FAT 16, FAT 32

MEDIA PLAYER

Playback format	MP3, WMA, WAV, FLAC
MP3 Title display	ID3-tag (version 2), file/folder
MP3 folder/file browsing	• (w/ track interruption)
MP3 file search	• (by file number)
Fast list browsing	• (via volume encoder)
Display modes	All mode (elapsed time, file, folder, song, artist, album)
Display of characters	File name up to 30
Variable display scrolling	• (always on if > 8 digits)
Bitrate (kBit/s)	32 – 320

EQUALIZER

Sound presets	Rock, pop, classic
---------------	--------------------

AMPLIFIER

Number of channels	4
Max. power	4 x 20 Watt
Sinus power at 14.4 V	4 x 7 Watt

DISPLAY

Type	Segment (1-line)
Digits	8
Color	negative black and white
Clock display	24 hours

INPUTS

Antenna (number of, type)	1, Motorola
USB (number of, type)	1 (front / standard A-type)
Aux-in (number of, type)	1 Front (3.5 mm jack)

OUTPUTS

Loudspeaker (number)	4
Pre-amplifier	2-channel (0.8V), Cinch

GENERAL

Software update	via USB
Menu language	English
User Manual languages	en, es, pt
Front panel	fixed panel
Panel/ decor ring color	black/chrome
Encoder / key illumination	White/white
Installation location	1-DIN-slot
Weight (kg)	ca. 1.26
Height x Width x Depth (mm)	50 x 178 x 164